Prism - Microservices Infrastructure

[PDF generated June 03 2025. For all recent updates please see the Nutanix Bible releases notes located at https:// nutanixbible.com/release_notes.html. Disclaimer: Downloaded PDFs may not always contain the latest information.]

Microservices Infrastructure (MSP) provides a common framework for delivering microservices associated with Prism Centralbased components such as Flow Virtual Networking, Objects, and the Security Dashboard. MSP also provides services such as Identity and Access Management and internal service load balancing.

Before MSP, Prism Central was a monolithic application. With MSP enabled, certain services are migrated and spun up in a Kubernetes (K8s) cluster as pods. Over time, most of the Prism Central services will be migrated and converted to microservices leveraging the common platform. This will enable services to be upgraded independently through LCM, so particular services can be upgraded without having to upgrade the entire PC instance, resulting in faster upgrades and quick patch updates.

As of PC.2022.9, the Microservices Infrastructure is enabled by default. When you upgrade to the latest version of Prism Central, MSP will be automatically enabled. Refer to the Prism Central MSP documentation for the full list of prerequisites and considerations.

Network Configuration

When MSP is enabled, a Kubernetes cluster is created on Prism Central. This Kubernetes cluster is one node with a standalone Prism Central and three nodes with a scale-out Prism Central.

MSP uses the following subnets.

|| |Subnet|Purpose| |10.100.0.0/16|Reserved for K8s pod network| |10.200.32.0/24|K8s Services (Flow Virtual Networking, IAM, etc)| | 10.200.0.0/16|Reserved for K8s Services network| |10.100.0.0/24|K8s pod - PC1| |10.100.1.0/24|K8s pod - PC2| |10.100.2.0/24|K8s pod -PC3|

If you already use these subnets for DNS or Active Directory and require different IP ranges, contact Nutanix Support.

On the firewall, bidirectional traffic should be allowed between Prism Central and:

- All of the Prism Element CVM IPs
- Prism Element Virtual IPs
- Prism Element Data Services IPs

On TCP ports:

- · 3205 iSCSI data plane connection
- \cdot 3260 iSCSI control plane connection
- 9440 Prism UI/API

Additionally, Prism Central should be able to ping all the Prism Element CVM IPs and Prism Element Virtual IPs.

During deployment, Prism Central must access several cloud services over port 443. For the most up-to-date list and diagrams, refer to the Ports & Protocols page on the Support Portal. There is also a dark site method of deployment for networks without Internet access, which is covered in the Prism Central MSP documentation.

When deploying Prism Central or enabling MSP, there are two options for the internal network configuration.

- Private Network (default): an internal private network is deployed using VXLAN for Kubernetes node communication. The default settings use 192.168.5.0/24. This requires no additional IPs from the physical network.
- VLAN Network: a managed or unmanaged VLAN network that has been configured on the Nutanix cluster. Five IPs are needed from the physical network for a single-node PC setup and 10 IPs are needed for a three-node scale-out PC setup. This option will add a second NIC to every PC VM for Kubernetes node communication.

		Prism Central Deployment	×
1 2 3	PC version Scale type Configuration	Please enter the Prism Central domain name, select a network and provide the required inputs to enable the Microservices Infrastructure.	
4	Microservices	prism-central.cluster.local	
5	Summary	Internal Network Private Network [default]	:
		Use default settings (recommended)	
		255.255.255.0	
		Gateway IP Address	
		192.168.5.1	
		IP Address Range (5 IPs needed)	
		192.168.5.2 - 192.168.5.64	
		Please ensure that the entered IP address range does not conflict with any reserved IPs (e.g. DHCP IP Pool) in your network.	
•	Back	Cancel	t

Microservices Setup During Prism Central Deployment

Architecture

The diagrams below assume the default private VXLAN network.

An example architecture diagram for the Kubernetes node on a single-PC deployment looks like the following. Note that the example does not show every service running in the Kubernetes cluster.

In this example, 10.10.250.50 is the IP address assigned to the PC VM and 10.100.0.0/24 is used as the network for the Kubernetes pod.

Prism Central VM	tanix Cluster	
Kubernetes Pods CIDR: 10.100.0.0/24 Pods 10.100.0.1/24 eth1	Prism Central VM	
Kubernetes Pod's CIDR: 10:000.0.0/24 Pods 10:100.0.1/24 enth 10:10.250.50		
Pods 10:100.0.1/24 enh eth 10:10.250.50	Kubernetes Pod's CIDR: 10.10	0.0.0/24
10.100.0.1/24 cni0 eth1		Pods
eth1		
eth1		10.100.0.1/24 cni0
eth1		
10.10.250.50 eth0		ethl
10.10.250.50 eth0		
		10.10.250.50 eth0

Single Node PC

For scale-out PC, two additional Kubernetes nodes are provisioned and they use the 10.100.1.0/24 and 10.100.2.0/24 networks for their pods, respectively.

Prism Central VM 1	Prism Central VM 2	Prism Central VM 3
Kubernetes Podis CIDR: 10100.0.0/24	Kubernetes Pod's CIDR: 10.100.1.0/24	Kubernetes Pedis CIDR: 10.100.2.0/24
Pods	Pods	Pods
10100.01/24 cn/0	10.100.11/24 cni0	10100.21/24 cni0
VXLAN 192168 S 0/24 ech1	eth	ethi
10.10.250.50	1010.250.51	1010.250.52

Scale-out PC

In a scale-out PC setup with VXLAN, pod-to-pod traffic across nodes uses direct routing and is encapsulated using the Prism Central VM IP.



Traffic from a pod on PC VM 1 to a pod on PC VM 3